Rittal - The System.

Faster – better – everywhere.





RX 9363.005 RiLineX NH fuse-switch disconnector

State: 15.12.2025 (Source: rittal.com/bg-bg)



RX 9363.005 - RiLineX NH fuse-switch disconnector

RiLineX NH fuse-switch disconnector in size 00 for mounting plates. The cover can be locked and prepared for a lead seal. It also has visual fuse monitoring. Integrated measuring points on the cover ensure safe voltage testing. NH fuse-switch disconnectors have a park position to make maintenance easier. Size M8 screw terminal connection. Includes electronic fuse monitoring.





Features

Model No.	RX 9363.005
Design	For mounting plate assembly
Benefits	Cover: can be locked and prepared for a lead seal
	Voltage test through separate opening
	Tool-free changeover of the cable outlet
	Park position for simpler maintenance work
	All variants also available with electronic fuse monitoring
Material	Polyamide (PA 6)
	Fire protection corresponding to UL 94
	Contact tracks: Electrolytic copper, silver-plated
Colour	RAL 9005
	RAL 35745
Supply includes	Connectors for electronic fuse monitoring
for mounting plate assembly	Yes
Cable outlet	Top/bottom

© Rittal 2025 2

Features

Type of electrical connection	Screw M8
Rated insulation voltage	1000 kV
Rated current max.	160 A
Rated operating current max.	160 A
Rated operating voltage	690 V AC
For NH size	00
Test specification	IEC/DIN EN 60 947-3 DIN EN 60 269-2 (fuse inserts)
Dimensions	Width: 106 mm Height: 228.9 mm Depth: 86.1 mm
Operating temperature range	-5 °C35 °C
Storage temperature range	-25 °C70 °C
Number of poles	3-pole
Utilisation category	AC-23B (400 V/100 A) AC-22B (500 V/100 A) DC-22B (250 V/100 A)
Contamination level	3
with electronic fuse monitoring	Yes
IP protection category to IEC 60 529	IP 2XB
Fire load	13,24 MJ/m²
Power dissipation (max.)	16 W
Packs of	1 pc(s).
Net weight	0.82
Gross weight	0.917
Copper weight (kg per piece)	0.18
Customs tariff number	85369095
ETIM 9	EC001040

© Rittal 2025 3

Approvals

Explanations

Declaration of conformity

© Rittal 2025