

# Rittal – The System.

Faster – better – everywhere.



## SV 9677.875 Current transformer

State: 21/05/2026 (Source: [rittal.com/gr-en](http://rittal.com/gr-en))

ENCLOSURES

POWER DISTRIBUTION

CLIMATE CONTROL

IT INFRASTRUCTURE

SOFTWARE & SERVICES

FRIEDHELM LOH GROUP



# SV 9677.875 - Current transformer

For inductive measurement of current flow.

## Features

|                                |  |
|--------------------------------|--|
| Model No.                      | SV 9677.875  |
| Product description            | Compact design without altering the installation depth via mechanical integration into the top-mounting components (185 mm centre-to-centre spacing); this allows space-saving assembly. |
| Material                       | Polyamide  |
| For size                       | 2/3  |
| To fit Model No.               | 9677.200<br>9677.210<br>9677.215<br>9677.300<br>9677.310<br>9677.315<br>9677.340<br>9677.770<br>9677.780<br>9677.900   |
| Rated power input              | 2.5 VA   |
| Type of electrical connection  | Box terminal   |
| Insulation material (class)    | B  |
| Primary current                | 400 A  |
| Secondary current              | 5 A  |
| Accuracy Class                 | 1  |
| Test specification             | IEC 60 044-1<br>EN 60715<br>DIN VDE 0414<br>DIN 42 600-2   |
| Connection of round conductors | 2.5 - 4 mm <sup>2</sup>  |

# Features

|                       |  |
|-----------------------|--|
| Rated frequency       | 50 - 60 Hz   |
| Packs of              | 1 pc(s).   |
| Net weight            | 0.13 kg  |
| Gross weight          | 0.172 kg   |
| Customs tariff number | 85044087   |
| ETIM 9                | EC002048   |
| ECLASS 8.0            | 27141146   |
| Product description   | SV current transformer 400 A/5 A for NH slimline fuse-switch disconnecter size 2-3 (SV 9677.XXX) |