

Faster – better – everywhere.





RX 9362.000 RiLineX NH fuse-switch disconnector

State: 9/09/2025 (Source: rittal.com/nz-en)

POWER DISTRIBUTION CLIMATE CONTROL





FRIEDHELM LOH GROUP

ENCLOSURES

RX 9362.000 - RiLineX NH fuse-switch disconnector

RiLineX NH fuse-switch disconnector in size 00 for 60 mm busbar systems. The cover can be locked and prepared for a lead seal. It also has visual fuse monitoring. Integrated measuring points on the cover ensure safe voltage testing. NH fuse-switch disconnectors have a park position to make maintenance easier. Size M8 screw terminal connection. Cable outlet can be at the top or bottom, as required.



Features

Model No.	RX 9362.000
Benefits	Cover: can be locked and prepared for a lead seal
	Voltage test through separate opening
	Snap-on mounting up to 250 A and simple adjustment to busbar
	thickness 5/10 mm
	Tool-free changeover of the cable outlet
	Park position for simpler maintenance work
	All variants also available with electronic fuse monitoring
Material	Polyamide (PA 6)
	Fire protection corresponding to UL 94
	Contact tracks: Electrolytic copper, silver-plated
Colour	RAL 9005
	RAL 35745
For bar systems with centre-to- centre spacing	60 mm
Cable outlet	Top/bottom
Type of electrical connection	Screw M8
Rated operating current max.	160 A
Rated operating voltage	690 V AC

Features

For NH size	00
Test specification	IEC/DIN EN 60 947-3 DIN EN 60 269-2 (fuse inserts)
Dimensions	Width: 106 mm Height: 195 mm Depth: 105 mm
Operating temperature range	-5 °C35 °C
Storage temperature range	-25 °C70 °C
To fit busbars	15 x 5/10 20 x 5/10 30 x 5/10
To fit busbar system	RiLine60 RiLineX
Number of poles	3-pole
Utilisation category	AC-23B (400 V/100 A) AC-22B (500 V/100 A) DC-22B (250 V/100 A)
Contamination level	3
IP protection category to IEC 60 529	IP 2XB
Power dissipation (max.)	19 W
Packs of	1 pc(s).
Net weight	1.015
Gross weight	1.023
Copper weight (kg per piece)	0.363
Customs tariff number	85369095
ETIM 9	EC001040



Explanations

Declaration of conformity