

RITTAL GmbH & Co. KG

AUF DEM STÜTZELBERG
D-35745 Herborn

<http://www.rittal.de>



MODEL	SK3336.470 KRAE0320TT00V000EG	POWER SUPPLY	: 400V 3 50Hz - 460V 3 60Hz
DRAWING NUMBER	EP22016 -	AUXILIARY SUPPLY	24VAC
CODE		CUSTOMER	
		REFERENCE	
CREATED THE	25/02/2022	FF2	
CHANGED ON THE			NUMBER OF PAGES 36

&EAB/1

CREATED BY	FF2	ON THE	25/02/2022	 RITTAL GmbH & Co. KG	SK3336.470 KRAE0320TT00V000EG COVER	DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
REVISOR		ON THE	LAST REVISION			CABINET CODE		3LP8_CARTRIT_ST	
								PAGES COUNTER	1
						&EAA	=	+	1

PAGE OVERVIEW

ZLP8_PAGKEL			
PAGE	DESIGNATION	DATE REVISION	REVISOR
&EAA/1	COVER		
&EAB/1	PAGE OVERVIEW		
&EAB/2	PAGE OVERVIEW		
&EAB/3	PAGE OVERVIEW		
&EAB/4	PAGE OVERVIEW		
&EFS=PWC+EC01/1	POWER WIRING		
&EFS=PWC+EC01/2	POWER WIRING		
&EFS=AUA+EC01/1	AUXILIARY WIRING		
&EFS=AUA+EC01/2	AUXILIARY WIRING		
&EFS=AUA+EC01/3	AUXILIARY WIRING		
&EFS=AUA+EC01/4	AUXILIARY WIRING		
&EFS=AIN+EC01/1	AUXILIARY WIRING		
&EFS=ISN+EC01/1	IN/OUT SIGNALS		
&EMZ+EC01/1	UPC OVERVIEW		
&EMZ+EC01/2	PCOE I/O OVERVIEW		
&EMA/1	TERMINAL STRIP SUMMARY +EC01-X2-+EC01-X10		

&EAA/1

2

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
PAGE OVERVIEW

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		ZLP8_CARTRIT_ST	
		PAGES COUNTER	2
		NUMBER OF PAGES	36
&EAB	=	+	1

PAGE OVERVIEW

ZLP8_PAGKEL			
PAGE	DESIGNATION	DATE REVISION	REVISOR
&EAA/1	COVER		
&EAB/1	PAGE OVERVIEW		
&EAB/2	PAGE OVERVIEW		
&EAB/3	PAGE OVERVIEW		
&EAB/4	PAGE OVERVIEW		
&EAB/5	PAGE OVERVIEW		
&EAB/6	PAGE OVERVIEW		
&EFS=PWC+EC01/1	POWER WIRING		
&EFS=PWC+EC01/2	POWER WIRING		
&EFS=AUA+EC01/1	AUXILIARY WIRING		
&EFS=AUA+EC01/2	AUXILIARY WIRING		
&EFS=AUA+EC01/3	AUXILIARY WIRING		
&EFS=AUA+EC01/4	AUXILIARY WIRING		
&EFS=AIN+EC01/1	AUXILIARY WIRING		
&EFS=ISN+EC01/1	IN/OUT SIGNALS		
&EMZ+EC01/1	UPC OVERVIEW		

PAGE OVERVIEW

ZLP8_PAGKEL			
PAGE	DESIGNATION	DATE REVISION	REVISOR
&EMA/2	TERMINAL DIAGRAM +EC01-X2		
&EMA/3	TERMINAL DIAGRAM +EC01-X2		
&EMA/4	TERMINAL DIAGRAM +EC01-X3		
&EMA/5	TERMINAL DIAGRAM +EC01-X2		
&EMA/6	TERMINAL DIAGRAM +EC01-X2		
&EMB/1	CABLE OVERVIEW =PWC+EC01-W0-=ISN+EC01-W21		
&EPC/1	BILL OF MATERIAL		
&EPC/2	BILL OF MATERIAL		
&EPC/3	BILL OF MATERIAL		
&EPC/4	BILL OF MATERIAL		
&EPC/5	BILL OF MATERIAL		
&EPC/6	BILL OF MATERIAL		
&EPC/7	BILL OF MATERIAL		
&EPC/8	BILL OF MATERIAL		
&EPC/9	BILL OF MATERIAL		
&EPC/10	BILL OF MATERIAL		

PAGE OVERVIEW
















































ZLP8_PAGKEL			
PAGE	DESIGNATION	DATE REVISION	REVISOR
&EPC/11	BILL OF MATERIAL		
&EPC/12	BILL OF MATERIAL		

PAGE OVERVIEW


ZLP8_PAGKEL			
PAGE	DESIGNATION	DATE REVISION	REVISOR
&EMZ+EC01/2	PCOE I/O OVERVIEW		
&EMA/1	TERMINAL STRIP SUMMARY +EC01-X2-+EC01-X10		
&EMA/2	TERMINAL DIAGRAM +EC01-X2		
&EMA/3	TERMINAL DIAGRAM +EC01-X2		
&EMA/4	TERMINAL DIAGRAM +EC01-X3		
&EMA/5	TERMINAL DIAGRAM +EC01-X2		
&EMA/6	TERMINAL DIAGRAM +EC01-X2		
&EMB/1	CABLE OVERVIEW =PWC+EC01-W0-=ISN+EC01-W21		
&EPC/1	BILL OF MATERIAL		
&EPC/2	BILL OF MATERIAL		
&EPC/3	BILL OF MATERIAL		
&EPC/4	BILL OF MATERIAL		
&EPC/5	BILL OF MATERIAL		
&EPC/6	BILL OF MATERIAL		
&EPC/7	BILL OF MATERIAL		
&EPC/8	BILL OF MATERIAL		


PAGE OVERVIEW

ZLP8_PAGKEL			
PAGE	DESIGNATION	DATE REVISION	REVISOR
&EPC/9	BILL OF MATERIAL		
&EPC/10	BILL OF MATERIAL		
&EPC/11	BILL OF MATERIAL		
&EPC/12	BILL OF MATERIAL		











SERIAL COMMUNICATION
UPC <-> PCOE





=AIN/1

&EMZ=/1


CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
IN/OUT SIGNALS

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		3LP8_CARTRIT_ST	15
		PAGES COUNTER	36
		NUMBER OF PAGES	1



&EFS=ISN/1

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION






RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
UPC OVERVIEW

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		3LP8_CARTRIT_ST	
PAGES COUNTER			16
NUMBER OF PAGES			36
&EMZ	=	+EC01	1

-P1.1



TERMINAL STRIP SUMMARY

2LP8_INMORKEL

STRIP DESIGNATION	TEXT OF THE STRIP DEFINITION	TERMINALS					GRAPHICS PAGE OF THE TERMINAL STRIP
		FIRST	LAST	SUM OF ALL	SUM OF ALL	TOTAL NUMBER	
				PE	N		
+EC01-X2		20	49	0	0	30	&EMA/2
+EC01-X3		80	83	0	0	4	&EMA/4
+EC01-X10		PE	PE	1	0	1	

TERMINAL DIAGRAM

PAGE / PATH		&EFS=ISN/1.2	&EFS=ISN/1.3	&EFS=AUA/1.5	&EFS=AUA/1.6	&EFS=AUA/1.7	&EFS=AUA/1.5	&EFS=AUA/1.6	&EFS=AUA/1.7	&EFS=AUA/2.8	&EFS=AUA/2.8	&EFS=AUA/2.9	&EFS=AUA/2.9	&EFS=AUA/3.7	&EFS=AUA/3.8	&EFS=AUA/3.9
TERM. CROSS SECTION		2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²
CABLE NAME																
CONNECTION		2						A1								
		-F5						-KA2								
		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
		●	●	●	●	●	●	I	I	I	I	●	●	I	●	●
		20	21	22	23	24	25	26	27	28	29	30	31	32	33	34
CABLE NAME																
		=AUA-W15														BK
		=AUA-W14	OIL RESISTANT UR												1	
		=AUA-W13	OIL RESISTANT UR											1		
		=AUA-W12	OIL RESISTANT UR									2	1			
		=AUA-W11	OIL RESISTANT UR							1	2					
		=AUA-W9					BK									
		=AUA-W8	OIL RESISTANT UR		1				2							
		=AUA-W7	OIL RESISTANT UR			1										
		=ISN-W21	OIL RESISTANT UR	1	2											
CONNECTION																
		1	2													
EXT DESIGN		-S11	-S12	-PA2	-PA1	-FL	-PA2	-PA1	-FL	-Y1	-Y1	-Y2	-Y2	-PB1	-PB2	-LE
STRIP DESIGNATION +EC01-X2		REMOTE ON/OFF	REMOTE ON/OFF	HIGH PRESSURE SWITCH	HIGH PRESSURE SWITCH	WATER LEVEL	HIGH PRESSURE SWITCH	HIGH PRESSURE SWITCH	WATER LEVEL	GAS VALVE 1 (+)	GAS VALVE 1 (-)	GAS VALVE 2 (-)	GAS VALVE 2 (+)	LOW PRESSURE SWITCH 1	LOW PRESSURE SWITCH 2	WATER LEVEL

TERMINAL DIAGRAM

PAGE / PATH		&EFS=ISN/1.2	&EFS=ISN/1.3	&EFS=AUA/1.5	&EFS=AUA/1.6	&EFS=AUA/1.7	&EFS=AUA/1.5	&EFS=AUA/1.6	&EFS=AUA/1.7	&EFS=AUA/2.8	&EFS=AUA/2.8	&EFS=AUA/2.9	&EFS=AUA/2.9	&EFS=AUA/3.7	&EFS=AUA/3.8	&EFS=AUA/3.9
TERM. CROSS SECTION		2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²
CABLE NAME																
CONNECTION		2						A1								
		-F5						-KA2								
		0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
		●	●	●	●	●	●	I	I	I	I	●	●	I	●	●
		20	21	22	23	24	25	26	27	28	29	30	31	32	33	34
CABLE NAME																
		=AUA-W15														BK
		=AUA-W14	OIL RESISTANT UR												1	
		=AUA-W13	OIL RESISTANT UR											1		
		=AUA-W12	OIL RESISTANT UR									2	1			
		=AUA-W11	OIL RESISTANT UR							1	2					
		=AUA-W9					BK									
		=AUA-W8	OIL RESISTANT UR		1				2							
		=AUA-W7	OIL RESISTANT UR			1		2								
		=ISN-W21	OIL RESISTANT UR	1	2											
STRIP DESIGNATION +EC01-X2		CONNECTION					1				2	1	2	2	1	
		EXT DESIGN	-S11	-S12	-PA2	-PA1	-FL	-PA2	-PA1	-FL	-Y1	-Y1	-Y2	-Y2	-PB1	-PB2
REMOTE ON/OFF																
REMOTE ON/OFF																
HIGH PRESSURE SWITCH																
HIGH PRESSURE SWITCH																
WATER LEVEL																
HIGH PRESSURE SWITCH																
HIGH PRESSURE SWITCH																
WATER LEVEL																
GAS VALVE 1 (+)																
GAS VALVE 1 (-)																
GAS VALVE 2 (-)																
GAS VALVE 2 (+)																
LOW PRESSURE SWITCH 1																
LOW PRESSURE SWITCH 2																
WATER LEVEL																

TERMINAL DIAGRAM

		PAGE / PATH		&EFS=PWC/2.2	&EFS=PWC/2.2	&EFS=PWC/2.4	&EFS=PWC/2.4												
		TERM. CROSS SECTION		2.5 mm²	2.5 mm²	2.5 mm²	2.5 mm²												
CABLE NAME																			
			CONNECTION	22		.2		22		.2									
			INT DESIGN	-K1		-K1		-K2		-K2									
			LEVEL	0		0		0		0									
			JUMPERS	I		I		I		I									
			TERMINAL NUMBER	80		81		82		83									
	=PWC-W6	OIL RESISTANT UR					1		2										
	=PWC-W5	OIL RESISTANT UR		1		2													
STRIP DESIGNATION +EC01-X3		CONNECTION	1		2		1		2										
		EXT DESIGN	-XB1		-XB1		-XB2		-XB2										
			CRANKCASE HEATER		CRANKCASE HEATER		CRANKCASE HEATER		CRANKCASE HEATER										

TERMINAL DIAGRAM

0123456789

TERMINAL DIAGRAM

STRIP DESIGNATION	+EC01-X2	CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
		CABLE NAME			CABLE NAME																				
PAGE / PATH		TERM. CROSS SECTION		&EFS=AUA/3.7		&EFS=AUA/3.8		&EFS=AUA/3.9		&EFS=AIN/1.3		&EFS=AIN/1.4		&EFS=AIN/1.5		&EFS=AIN/1.6		&EFS=ISN/1.3		&EFS=ISN/1.4		&EFS=ISN/1.5		&EFS=ISN/1.5	
				2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²		2.5 mm²	

TERMINAL DIAGRAM

		PAGE / PATH	&EFS=AUA/3.7	&EFS=AUA/3.8	&EFS=AUA/3.9	&EFS=AIN/1.3	&EFS=AIN/1.4	&EFS=AIN/1.5	&EFS=AIN/1.6	&EFS=AIN/1.3	&EFS=AIN/1.4	&EFS=AIN/1.5	&EFS=AIN/1.6	&EFS=ISN/1.3	&EFS=ISN/1.4	&EFS=ISN/1.5	&EFS=ISN/1.5	
		TERM. CROSS SECTION	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	2.5 mm ²	
CABLE NAME																		
		CONNECTION	J4:DI6															
		INT DESIGN	-P1															
		LEVEL	0				0	0	0	0	0	0	0	0	0	0	0	0
		JUMPERS	I				●	●	●	●	I	I	I	I	I	I	I	I
		TERMINAL NUMBER	35				38	39	40	41	42	43	44	45	46	47	48	49
CABLE NAME																		
	=ISN-W21	OIL RESISTANT UR												3	4	5	6	
	=AIN-W20	TPE							BK				WH					
	=AIN-W19	TPE						BK				WH						
	=AIN-W18	TPE					BK				WH							
	=AIN-W17	TPE				BK				WH								
	=AUA-W15				BN													
	=AUA-W14	OIL RESISTANT UR		2														
=AUA-W13	OIL RESISTANT UR	2																
STRIP DESIGNATION + EC01-X2		CONNECTION																
		EXT DESIGN	-PB1			-LE	-B1	-B2	-B1.3	-B2.3	-B1	-B2	-B1.3	-B2.3	-SI3	-SI4	-SI5	-SI6
LOW PRESSURE SWITCH 1																		
LOW PRESSURE SWITCH 2																		
WATER LEVEL																		
OUTLET PROBE																		
AMBIENT PROBE																		
ANTIFREEZE PROBE 1																		
ANTIFREEZE PROBE 2																		
OUTLET PROBE																		
AMBIENT PROBE																		
ANTIFREEZE PROBE 1																		
ANTIFREEZE PROBE 2																		
COMMON																		
WARNING SIGNAL																		
ALARM SIGNAL																		
TEMPERATURE ALARM																		

CABLE OVERVIEW

2LP8_CAVIKEL

[illegible]

&EMA/6

&EPC/1

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
=AIN+EC01-B1	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.3
=AIN+EC01-B1.3	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.5
=AIN+EC01-B2	1		NTC060WP00	NTC PROBE, IP68, CABLE 6m, -50/+105°C	CAREL	903061	&EFS=AIN+EC01/1.4
=AIN+EC01-B2.3	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.6
=AUA+EC01-DS	1		927206	GR DISPLAY TOUCH BLU-E CHILLER	CAREL	927206	&EFS=AUA+EC01/2.4
=PWC+EC01-F1	1		5SY6214-7	CIRCUIT BREAKER 6KA 2POL C0.3	Siemens	905359	&EFS=PWC+EC01/2.2
=PWC+EC01-F2	1		5SY6214-7	CIRCUIT BREAKER 6KA 2POL C0.3	Siemens	905359	&EFS=PWC+EC01/2.4
=PWC+EC01-F3	1		5SY6202-7	CIRCUIT BREAKER 6KA 2POL C2	Siemens	906346	&EFS=PWC+EC01/2.6
=PWC+EC01-F4	1		5SY6314-7	CIRCUIT BREAKER 6KA 3POL C0.3	Siemens	918236	&EFS=PWC+EC01/2.8
=AUA+EC01-F5	1		5SY6108-7	CIRCUIT BREAKER 6KA 1POL C8	Siemens	907350	&EFS=AUA+EC01/1.1
=AUA+EC01-G2	1		AKAS0036024012	DC/DC CONVERTER 24V/12V 3A	ELMAS	927063	&EFS=AUA+EC01/2.6
+EC01-GND	10			SCREW TC M5x10 ZN-ST 4.8	---	915741	
+EC01-GND	31				KELVIN		(AMB.S1)
+EC01-GND_CB	1				KELVIN		(AMB.S1)
+EC01-GND_DO	1			SCREW TE M8X25 ST-ZN	---	207930	(AMB.S1)
+EC01-GND_MP	1			SCREW TE M8X30 ST-ZN	---	206543	(AMB.S1)
=AUA+EC01-K1	1		3RT2027-1AC20	CONTACTOR,AC3:15KW 1NO+1NC AC24V 50/60HZ	Siemens	920111	&EFS=AUA+EC01/2.1
=AUA+EC01-K1	1		3RH29111HA01	AUX. SWITCH BLOCK , 1NC COND. PATHS: 1NC,	Siemens	924271	&EFS=AUA+EC01/2.1
=AUA+EC01-K1	1		3RA2921-1A	MAGN-SWITCH ACC SIEMENS 3RA2921-1A	Siemens	920187	&EFS=AUA+EC01/2.1
=AUA+EC01-K2	1		3RT2027-1AC20	CONTACTOR,AC3:15KW 1NO+1NC AC24V 50/60HZ	Siemens	920111	&EFS=AUA+EC01/2.2
=AUA+EC01-K2	1		3RH29111HA01	AUX. SWITCH BLOCK , 1NC COND. PATHS: 1NC,	Siemens	924271	&EFS=AUA+EC01/2.2
=AUA+EC01-K2	1		3RA2921-1A	MAGN-SWITCH ACC SIEMENS 3RA2921-1A	Siemens	920187	&EFS=AUA+EC01/2.2
=AUA+EC01-K3	1		3RT2015-1AB01	CONTACTOR,AC3:3KW 1NO AC24V 50/60HZ	Siemens	919835	&EFS=AUA+EC01/2.3
=AUA+EC01-K3	1		3RA1921-1D	LINK MODULE F.3RV S00/S0, 3RT S00	Siemens	920186	&EFS=AUA+EC01/2.3
=AUA+EC01-K4	1		3RT2016-1AB01	CONTACTOR,AC3:4KW 1NO AC24V 50/60HZ	Siemens	920015	&EFS=AUA+EC01/2.4
=AUA+EC01-K4	1		3RA1921-1D	LINK MODULE F.3RV S00/S0, 3RT S00	Siemens	920186	&EFS=AUA+EC01/2.4
=AUA+EC01-KA1	1		55.34.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 4 POLE, 7 A - AC (50/60 HZ) - 24 V	Finder	903668	&EFS=AUA+EC01/1.6
=AUA+EC01-KA1	1		94.74	SOCKET FOR 55.34 RELAY	Finder	903669	&EFS=AUA+EC01/1.6

&EMB/1

2

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		2LP8_CARTRIT_ST	25
		PAGES COUNTER	25
		NUMBER OF PAGES	36
&EPC	=	+	1

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
=AIN+EC01-B1	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.3
=AIN+EC01-B1.3	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.5
=AIN+EC01-B2	1		NTC060WP00	NTC PROBE, IP68, CABLE 6m, -50/+105°C	CAREL	903061	&EFS=AIN+EC01/1.4
=AIN+EC01-B2.3	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.6
=AUA+EC01-DS	1		927206	GR DISPLAY TOUCH BLU-E CHILLER	CAREL	927206	&EFS=AUA+EC01/2.4
=PWC+EC01-F1	1		SSY6214-7	CIRCUIT BREAKER 6KA 2POL C0.3	Siemens	905359	&EFS=PWC+EC01/2.2
=PWC+EC01-F2	1		SSY6214-7	CIRCUIT BREAKER 6KA 2POL C0.3	Siemens	905359	&EFS=PWC+EC01/2.4
=PWC+EC01-F3	1		SSY6202-7	CIRCUIT BREAKER 6KA 2POL C2	Siemens	906346	&EFS=PWC+EC01/2.6
=PWC+EC01-F4	1		SSY6314-7	CIRCUIT BREAKER 6KA 3POL C0.3	Siemens	918236	&EFS=PWC+EC01/2.8
=AUA+EC01-F5	1		SSY6108-7	CIRCUIT BREAKER 6KA 1POL C8	Siemens	907350	&EFS=AUA+EC01/1.1
=AUA+EC01-G2	1		AKAS0036024012	DC/DC CONVERTER 24V/12V 3A	ELMAS	927063	&EFS=AUA+EC01/2.6
+EC01-GND	10			SCREW TC M5x10 ZN-ST 4.8	---	915741	
+EC01-GND	31				KELVIN		(AMB.S1)
+EC01-GND_CB	1				KELVIN		(AMB.S1)
+EC01-GND_DO	1			SCREW TE M8X25 ST-ZN	---	207930	(AMB.S1)
+EC01-GND_MP	1			SCREW TE M8X30 ST-ZN	---	206543	(AMB.S1)
=AUA+EC01-K1	1		3RT2027-1AC20	CONTACTOR,AC3:15KW 1NO+1NC AC24V 50/60HZ	Siemens	920111	&EFS=AUA+EC01/2.1
=AUA+EC01-K1	1		3RH29111HA01	AUX. SWITCH BLOCK , 1NC COND. PATHS: 1NC,	Siemens	924271	&EFS=AUA+EC01/2.1
=AUA+EC01-K1	1		3RA2921-1A	MAGN-SWITCH ACC SIEMENS 3RA2921-1A	Siemens	920187	&EFS=AUA+EC01/2.1
=AUA+EC01-K2	1		3RT2027-1AC20	CONTACTOR,AC3:15KW 1NO+1NC AC24V 50/60HZ	Siemens	920111	&EFS=AUA+EC01/2.2
=AUA+EC01-K2	1		3RH29111HA01	AUX. SWITCH BLOCK , 1NC COND. PATHS: 1NC,	Siemens	924271	&EFS=AUA+EC01/2.2
=AUA+EC01-K2	1		3RA2921-1A	MAGN-SWITCH ACC SIEMENS 3RA2921-1A	Siemens	920187	&EFS=AUA+EC01/2.2
=AUA+EC01-K3	1		3RT2015-1AB01	CONTACTOR,AC3:3KW 1NO AC24V 50/60HZ	Siemens	919835	&EFS=AUA+EC01/2.3
=AUA+EC01-K3	1		3RA1921-1D	LINK MODULE F.3RV S00/S0, 3RT S00	Siemens	920186	&EFS=AUA+EC01/2.3
=AUA+EC01-K4	1		3RT2016-1AB01	CONTACTOR,AC3:4KW 1NO AC24V 50/60HZ	Siemens	920015	&EFS=AUA+EC01/2.4
=AUA+EC01-K4	1		3RA1921-1D	LINK MODULE F.3RV S00/S0, 3RT S00	Siemens	920186	&EFS=AUA+EC01/2.4
=AUA+EC01-KA1	1		55.34.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 4 POLE, 7 A - AC (50/60 HZ) - 24 V	Finder	903668	&EFS=AUA+EC01/1.6
=AUA+EC01-KA1	1		94.74	SOCKET FOR 55.34 RELAY	Finder	903669	&EFS=AUA+EC01/1.6

1

3

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		2LP8_CARTRIT_ST	
		PAGES COUNTER	26
		NUMBER OF PAGES	36
&EPC	=	+	2

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
=AIN+EC01-B1	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.3
=AIN+EC01-B1.3	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.5
=AIN+EC01-B2	1		NTC060WP00	NTC PROBE, IP68, CABLE 6m, -50/+105°C	CAREL	903061	&EFS=AIN+EC01/1.4
=AIN+EC01-B2.3	1		NTC030WP00	PROBE NTC, IP68, WIRE 3m, -50/+105°C	CAREL	903060	&EFS=AIN+EC01/1.6
=AUA+EC01-DS	1		927206	GR DISPLAY TOUCH BLU-E CHILLER	CAREL	927206	&EFS=AUA+EC01/2.4
=PWC+EC01-F1	1		5SY6214-7	CIRCUIT BREAKER 6KA 2POL C0.3	Siemens	905359	&EFS=PWC+EC01/2.2
=PWC+EC01-F2	1		5SY6214-7	CIRCUIT BREAKER 6KA 2POL C0.3	Siemens	905359	&EFS=PWC+EC01/2.4
=PWC+EC01-F3	1		5SY6202-7	CIRCUIT BREAKER 6KA 2POL C2	Siemens	906346	&EFS=PWC+EC01/2.6
=PWC+EC01-F4	1		5SY6314-7	CIRCUIT BREAKER 6KA 3POL C0.3	Siemens	918236	&EFS=PWC+EC01/2.8
=AUA+EC01-F5	1		5SY6108-7	CIRCUIT BREAKER 6KA 1POL C8	Siemens	907350	&EFS=AUA+EC01/1.1
=AUA+EC01-G2	1		AKAS0036024012	DC/DC CONVERTER 24V/12V 3A	ELMAS	927063	&EFS=AUA+EC01/2.6
+EC01-GND	10			SCREW TC M5x10 ZN-ST 4.8	---	915741	
+EC01-GND	31				KELVIN		(AMB.S1)
+EC01-GND_CB	1				KELVIN		(AMB.S1)
+EC01-GND_DO	1			SCREW TE M8X25 ST-ZN	---	207930	(AMB.S1)
+EC01-GND_MP	1			SCREW TE M8X30 ST-ZN	---	206543	(AMB.S1)
=AUA+EC01-K1	1		3RT2027-1AC20	CONTACTOR,AC3:15KW 1NO+1NC AC24V 50/60HZ	Siemens	920111	&EFS=AUA+EC01/2.1
=AUA+EC01-K1	1		3RH29111HA01	AUX. SWITCH BLOCK , 1NC COND. PATHS: 1NC,	Siemens	924271	&EFS=AUA+EC01/2.1
=AUA+EC01-K1	1		3RA2921-1A	MAGN-SWITCH ACC SIEMENS 3RA2921-1A	Siemens	920187	&EFS=AUA+EC01/2.1
=AUA+EC01-K2	1		3RT2027-1AC20	CONTACTOR,AC3:15KW 1NO+1NC AC24V 50/60HZ	Siemens	920111	&EFS=AUA+EC01/2.2
=AUA+EC01-K2	1		3RH29111HA01	AUX. SWITCH BLOCK , 1NC COND. PATHS: 1NC,	Siemens	924271	&EFS=AUA+EC01/2.2
=AUA+EC01-K2	1		3RA2921-1A	MAGN-SWITCH ACC SIEMENS 3RA2921-1A	Siemens	920187	&EFS=AUA+EC01/2.2
=AUA+EC01-K3	1		3RT2015-1AB01	CONTACTOR,AC3:3KW 1NO AC24V 50/60HZ	Siemens	919835	&EFS=AUA+EC01/2.3
=AUA+EC01-K3	1		3RA1921-1D	LINK MODULE F.3RV S00/S0, 3RT S00	Siemens	920186	&EFS=AUA+EC01/2.3
=AUA+EC01-K4	1		3RT2016-1AB01	CONTACTOR,AC3:4KW 1NO AC24V 50/60HZ	Siemens	920015	&EFS=AUA+EC01/2.4
=AUA+EC01-K4	1		3RA1921-1D	LINK MODULE F.3RV S00/S0, 3RT S00	Siemens	920186	&EFS=AUA+EC01/2.4
=AUA+EC01-KA1	1		55.34.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 4 POLE, 7 A - AC (50/60 HZ) - 24 V	Finder	903668	&EFS=AUA+EC01/1.6
=AUA+EC01-KA1	1		94.74	SOCKET FOR 55.34 RELAY	Finder	903669	&EFS=AUA+EC01/1.6

2

4

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		2LP8_CARTRIT_ST	27
&EPC	=	+	3

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
=AUA+EC01-KA2	1		55.34.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 4 POLE, 7 A - AC (50/60 HZ) - 24 V	Finder	903668	&EFS=AUA+EC01/1.5
=AUA+EC01-KA2	1		94.74	SOCKET FOR 55.34 RELAY	Finder	903669	&EFS=AUA+EC01/1.5
=AUA+EC01-KA3	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.4
=AUA+EC01-KA3	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.4
=AUA+EC01-KA4	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.3
=AUA+EC01-KA4	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.3
=AUA+EC01-KA5	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.2
=AUA+EC01-KA5	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.2
=PWC+EC01-KG	1		3UG4511-1AP20	PHASE CONTROL RELAY	Siemens	917383	&EFS=PWC+EC01/2.8
+EC01-P1	1		UP3B00200TBM0	TERMOREG PROGRAM CAREL UP3B00200TBM0	CAREL	928216	&EMZ+EC01/1.0
+EC01-P1	1		UP3CON0M00	TERMOREG ACCESS CAREL UP3CON0M00	CAREL	928217	&EMZ+EC01/1.0
+EC01-P1	1		PCO1000WD0	PCOWEB - ETHERNET INTERFACE	CAREL	921648	&EMZ+EC01/1.0
+EC01-P1.1	1		PCOE0004850	EXPANSION BOARD RS485	CAREL	911457	&EMZ+EC01/2.3
+EC01-P1.1	1		PCOECON000	PCOE SCREW PLUGS	CAREL	911569	&EMZ+EC01/2.3
=PWC+EC01-Q0	1		22003008	MANUALLY OPERATED AND MODULAR MULTIPOLAR LOAD BREAK SWITCHES	SOCOMEK	922908	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		1474 1111	RED KNOB TYPE S00	SOCOMEK	921673	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		1407 0532	OPERATING SHAFT 320mm	SOCOMEK	911759	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		2294 3009	3 POLE TERMINALS COVER 63...80	SOCOMEK	922909	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		2200 9009	GROUND POLE 63...80	SOCOMEK	925999	&EFS=PWC+EC01/1.0
=PWC+EC01-Q1	1		3RV2021-4BA15	CIRCUIT-BREAKER SCREW CONNECTION 20A	Siemens	920000	&EFS=PWC+EC01/1.2
=PWC+EC01-Q2	1		3RV2021-4BA15	CIRCUIT-BREAKER SCREW CONNECTION 20A	Siemens	920000	&EFS=PWC+EC01/1.4
=PWC+EC01-Q3	1		3RV2011-1EA15	CIRCUIT-BREAKER SCREW CONNECTION 4A	Siemens	919837	&EFS=PWC+EC01/1.5
=PWC+EC01-Q4	1		3RV2011-1HA15	CIRCUIT-BREAKER SCREW CONNECTION 8A	Siemens	919991	&EFS=PWC+EC01/1.7
=PWC+EC01-Q4	1		3RV2925-5AB	3-PHASE INFEEED TERMINAL SZ S0/S00	Siemens	920185	&EFS=PWC+EC01/1.7
=PWC+EC01-T1	1		TCN80000200.057	200VA 0-230-400-415-440-460-480/0-24	TECNOCABLAGGI	905560	&EFS=PWC+EC01/2.6
=AUA+EC01-TCONN	1		TCONN6J000	TRANSMISSION BOARD FOR PGD DISPLAY	CAREL	911363	&EFS=AUA+EC01/2.5
-U1	1		1058000	AX Compact enclosure, WHD: 600x800x250 mm, sheet steel	Rittal	1058000	(AMB.S1)
-U2	1	0,545m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)

3

5

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
CABINET CODE		2LP8_CARTRIT_ST	
&EPC	=	+	4
PAGES COUNTER		NUMBER OF PAGES	28
			36

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
-U3	1	0,545m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U4	1	0,425m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U5	1	0,325m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U6	1	0,325m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U7	1	0,325m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U8	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U9	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U12	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U13	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U14	1	0,255m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U15	1	0,255m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U50	1		249-116	Screwless end stop	WAGO	904502	(AMB.S1)
-U51	1		249-116	Screwless end stop	WAGO	904502	(AMB.S1)
-U136	1		2564300	SZ Plastic gland plates, Size 4	Rittal	2564300	(AMB.S1)
-U137	1			STAND OFFS H Fx F 19x25x5 PE	---	909454	(AMB.S1)
-U138	1			STAND OFFS H Fx F 19x25x5 PE	---	909454	(AMB.S1)
-U234	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U235	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U236	1	0,425m		DIN RAIL OMEGA 35x7,5	---	905499	(AMB.S1)
=AUA+EC01-V1	1		3RT29261BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919431	&EFS=AUA+EC01/2.1
=AUA+EC01-V2	1		3RT29261BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919431	&EFS=AUA+EC01/2.2
=AUA+EC01-V3	1		3RT29161BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919432	&EFS=AUA+EC01/2.3
=AUA+EC01-V4	1		3RT29161BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919432	&EFS=AUA+EC01/2.4
-W1	1	0,56m		CU BAR 12X3	---	909453	(AMB.S1)
=PWC+EC01-WQD	1		3RV1915-1CB	3-PHASE BUSBARS	Siemens	909358	&EFS=PWC+EC01/1.2
+EC01-X2	1		249-116	Screwless end stop	WAGO	904502	
+EC01-X2	2		280-309	End and intermediate plate	WAGO	904525	&EFS=ISN+EC01/1.5
+EC01-X2	30		280-901	2-conductor through terminal block	WAGO	903680	

4

6

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
		2LP8_CARTRIT_ST	
CABINET CODE		PAGES COUNTER	29
		NUMBER OF PAGES	36
&EPC	=	+	5

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
=AUA+EC01-KA2	1		55.34.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 4 POLE, 7 A - AC (50/60 HZ) - 24 V	Finder	903668	&EFS=AUA+EC01/1.5
=AUA+EC01-KA2	1		94.74	SOCKET FOR 55.34 RELAY	Finder	903669	&EFS=AUA+EC01/1.5
=AUA+EC01-KA3	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.4
=AUA+EC01-KA3	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.4
=AUA+EC01-KA4	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.3
=AUA+EC01-KA4	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.3
=AUA+EC01-KA5	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.2
=AUA+EC01-KA5	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.2
=PWC+EC01-KG	1		3UG4511-1AP20	PHASE CONTROL RELAY	Siemens	917383	&EFS=PWC+EC01/2.8
+EC01-P1	1		UP3B00200TBM0	TERMOREG PROGRAM CAREL UP3B00200TBM0	CAREL	928216	&EMZ+EC01/1.0
+EC01-P1	1		UP3CON0M00	TERMOREG ACCESS CAREL UP3CON0M00	CAREL	928217	&EMZ+EC01/1.0
+EC01-P1	1		PCO1000WD0	PCOWEB - ETHERNET INTERFACE	CAREL	921648	&EMZ+EC01/1.0
+EC01-P1.1	1		PCOE0004850	EXPANSION BOARD RS485	CAREL	911457	&EMZ+EC01/2.3
+EC01-P1.1	1		PCOECON000	PCOE SCREW PLUGS	CAREL	911569	&EMZ+EC01/2.3
=PWC+EC01-Q0	1		22003008	MANUALLY OPERATED AND MODULAR MULTIPOLAR LOAD BREAK SWITCHES	SOCOMEK	922908	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		1474 1111	RED KNOB TYPE S00	SOCOMEK	921673	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		1407 0532	OPERATING SHAFT 320mm	SOCOMEK	911759	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		2294 3009	3 POLE TERMINALS COVER 63...80	SOCOMEK	922909	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		2200 9009	GROUND POLE 63...80	SOCOMEK	925999	&EFS=PWC+EC01/1.0
=PWC+EC01-Q1	1		3RV2021-4BA15	CIRCUIT-BREAKER SCREW CONNECTION 20A	Siemens	920000	&EFS=PWC+EC01/1.2
=PWC+EC01-Q2	1		3RV2021-4BA15	CIRCUIT-BREAKER SCREW CONNECTION 20A	Siemens	920000	&EFS=PWC+EC01/1.4
=PWC+EC01-Q3	1		3RV2011-1EA15	CIRCUIT-BREAKER SCREW CONNECTION 4A	Siemens	919837	&EFS=PWC+EC01/1.5
=PWC+EC01-Q4	1		3RV2011-1HA15	CIRCUIT-BREAKER SCREW CONNECTION 8A	Siemens	919991	&EFS=PWC+EC01/1.7
=PWC+EC01-Q4	1		3RV2925-5AB	3-PHASE INFEEED TERMINAL SZ S0/S00	Siemens	920185	&EFS=PWC+EC01/1.7
=PWC+EC01-T1	1		TCN80000200.057	200VA 0-230-400-415-440-460-480/0-24	TECNOCABLAGGI	905560	&EFS=PWC+EC01/2.6
=AUA+EC01-TCONN	1		TCONN6J000	TRANSMISSION BOARD FOR PGD DISPLAY	CAREL	911363	&EFS=AUA+EC01/2.5
-U1	1		1058000	AX Compact enclosure, WHD: 600x800x250 mm, sheet steel	Rittal	1058000	(AMB.S1)
-U2	1	0,545m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
-U3	1	0,545m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U4	1	0,425m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U5	1	0,325m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U6	1	0,325m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U7	1	0,325m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U8	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U9	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U12	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U13	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U14	1	0,255m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U15	1	0,255m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U50	1		249-116	Screwless end stop	WAGO	904502	(AMB.S1)
-U51	1		249-116	Screwless end stop	WAGO	904502	(AMB.S1)
-U136	1		2564300	SZ Plastic gland plates, Size 4	Rittal	2564300	(AMB.S1)
-U137	1			STAND OFFS H Fx F 19x25x5 PE	---	909454	(AMB.S1)
-U138	1			STAND OFFS H Fx F 19x25x5 PE	---	909454	(AMB.S1)
-U234	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U235	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U236	1	0,425m		DIN RAIL OMEGA 35x7,5	---	905499	(AMB.S1)
=AUA+EC01-V1	1		3RT29261BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919431	&EFS=AUA+EC01/2.1
=AUA+EC01-V2	1		3RT29261BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919431	&EFS=AUA+EC01/2.2
=AUA+EC01-V3	1		3RT29161BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919432	&EFS=AUA+EC01/2.3
=AUA+EC01-V4	1		3RT29161BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919432	&EFS=AUA+EC01/2.4
-W1	1	0,56m		CU BAR 12X3	---	909453	(AMB.S1)
=PWC+EC01-WQD	1		3RV1915-1CB	3-PHASE BUSBARS	Siemens	909358	&EFS=PWC+EC01/1.2
+EC01-X2	1		249-116	Screwless end stop	WAGO	904502	
+EC01-X2	2		280-309	End and intermediate plate	WAGO	904525	&EFS=ISN+EC01/1.5
+EC01-X2	30		280-901	2-conductor through terminal block	WAGO	903680	

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL

GmbH & Co. KG

SK3336.470

KRAE0320TT00V000EG

BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
		2LP8_CARTRIT_ST	
CABINET CODE		PAGES COUNTER	32
		NUMBER OF PAGES	36
&EPC	=	+	8

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
=AUA+EC01-KA2	1		55.34.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 4 POLE, 7 A - AC (50/60 HZ) - 24 V	Finder	903668	&EFS=AUA+EC01/1.5
=AUA+EC01-KA2	1		94.74	SOCKET FOR 55.34 RELAY	Finder	903669	&EFS=AUA+EC01/1.5
=AUA+EC01-KA3	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.4
=AUA+EC01-KA3	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.4
=AUA+EC01-KA4	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.3
=AUA+EC01-KA4	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.3
=AUA+EC01-KA5	1		55.32.8.024.0040	MINIATURE GENERAL PURPOSE RELAY, 2 POLE, 10 A - AC (50/60 HZ) - 24 V	Finder	904571	&EFS=AUA+EC01/1.2
=AUA+EC01-KA5	1		94.82	SOCKET FOR 55.32 RELE'	Finder	904587	&EFS=AUA+EC01/1.2
=PWC+EC01-KG	1		3UG4511-1AP20	PHASE CONTROL RELAY	Siemens	917383	&EFS=PWC+EC01/2.8
+EC01-P1	1		UP3B00200TBM0	TERMOREG PROGRAM CAREL UP3B00200TBM0	CAREL	928216	&EMZ+EC01/1.0
+EC01-P1	1		UP3CON0M00	TERMOREG ACCESS CAREL UP3CON0M00	CAREL	928217	&EMZ+EC01/1.0
+EC01-P1	1		PCO1000WD0	PCOWEB - ETHERNET INTERFACE	CAREL	921648	&EMZ+EC01/1.0
+EC01-P1.1	1		PCOE0004850	EXPANSION BOARD RS485	CAREL	911457	&EMZ+EC01/2.3
+EC01-P1.1	1		PCOECON000	PCOE SCREW PLUGS	CAREL	911569	&EMZ+EC01/2.3
=PWC+EC01-Q0	1		22003008	MANUALLY OPERATED AND MODULAR MULTIPOLAR LOAD BREAK SWITCHES	SOCOMEK	922908	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		1474 1111	RED KNOB TYPE S00	SOCOMEK	921673	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		1407 0532	OPERATING SHAFT 320mm	SOCOMEK	911759	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		2294 3009	3 POLE TERMINALS COVER 63...80	SOCOMEK	922909	&EFS=PWC+EC01/1.0
=PWC+EC01-Q0	1		2200 9009	GROUND POLE 63...80	SOCOMEK	925999	&EFS=PWC+EC01/1.0
=PWC+EC01-Q1	1		3RV2021-4BA15	CIRCUIT-BREAKER SCREW CONNECTION 20A	Siemens	920000	&EFS=PWC+EC01/1.2
=PWC+EC01-Q2	1		3RV2021-4BA15	CIRCUIT-BREAKER SCREW CONNECTION 20A	Siemens	920000	&EFS=PWC+EC01/1.4
=PWC+EC01-Q3	1		3RV2011-1EA15	CIRCUIT-BREAKER SCREW CONNECTION 4A	Siemens	919837	&EFS=PWC+EC01/1.5
=PWC+EC01-Q4	1		3RV2011-1HA15	CIRCUIT-BREAKER SCREW CONNECTION 8A	Siemens	919991	&EFS=PWC+EC01/1.7
=PWC+EC01-Q4	1		3RV2925-5AB	3-PHASE INFEEED TERMINAL SZ S0/S00	Siemens	920185	&EFS=PWC+EC01/1.7
=PWC+EC01-T1	1		TCN80000200.057	200VA 0-230-400-415-440-460-480/0-24	TECNOCABLAGGI	905560	&EFS=PWC+EC01/2.6
=AUA+EC01-TCONN	1		TCONN6J000	TRANSMISSION BOARD FOR PGD DISPLAY	CAREL	911363	&EFS=AUA+EC01/2.5
-U1	1		1058000	AX Compact enclosure, WHD: 600x800x250 mm, sheet steel	Rittal	1058000	(AMB.S1)
-U2	1	0,545m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)

BILL OF MATERIALS



2LP8_RICKEL_20

DESIGNATION	AMOUNT	LENGTH	ARTICLE NUMBER	DESIGNATION 1	MANUFACTURER	INTERNAL NO	PAGE / PATH
-U3	1	0,545m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U4	1	0,425m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U5	1	0,325m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U6	1	0,325m		WIRING DUCT 40x80 PLASTIC 4X6	---	909700	(AMB.S1)
-U7	1	0,325m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U8	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U9	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U12	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U13	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U14	1	0,255m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U15	1	0,255m	2313750	SZ Support rail to EN 60 715, version TS 35/7,5, L: 2000 mm	Rittal	2313750	(AMB.S1)
-U50	1		249-116	Screwless end stop	WAGO	904502	(AMB.S1)
-U51	1		249-116	Screwless end stop	WAGO	904502	(AMB.S1)
-U136	1		2564300	SZ Plastic gland plates, Size 4	Rittal	2564300	(AMB.S1)
-U137	1			STAND OFFS H Fx F 19x25x5 PE	---	909454	(AMB.S1)
-U138	1			STAND OFFS H Fx F 19x25x5 PE	---	909454	(AMB.S1)
-U234	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U235	1			STAND OFFS H Mx F L20 M6 ZN-ST	---	904235	(AMB.S1)
-U236	1	0,425m		DIN RAIL OMEGA 35x7,5	---	905499	(AMB.S1)
=AUA+EC01-V1	1		3RT29261BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919431	&EFS=AUA+EC01/2.1
=AUA+EC01-V2	1		3RT29261BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919431	&EFS=AUA+EC01/2.2
=AUA+EC01-V3	1		3RT29161BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919432	&EFS=AUA+EC01/2.3
=AUA+EC01-V4	1		3RT29161BB00	SURGE SUPPRESSOR, VARISTOR,	Siemens	919432	&EFS=AUA+EC01/2.4
-W1	1	0,56m		CU BAR 12X3	---	909453	(AMB.S1)
=PWC+EC01-WQD	1		3RV1915-1CB	3-PHASE BUSBARS	Siemens	909358	&EFS=PWC+EC01/1.2
+EC01-X2	1		249-116	Screwless end stop	WAGO	904502	
+EC01-X2	2		280-309	End and intermediate plate	WAGO	904525	&EFS=ISN+EC01/1.5
+EC01-X2	30		280-901	2-conductor through terminal block	WAGO	903680	

10

12

CREATED BY	FF2	ON THE	25/02/2022
REVISOR		ON THE	LAST REVISION



RITTAL
GmbH & Co. KG

SK3336.470
KRAE0320TT00V000EG
BILL OF MATERIAL

DRAWING NUMBER	EP22016	EPLAN Electric P8	2022.0.3
		2LP8_CARTRIT_ST	
CABINET CODE		PAGES COUNTER	35
		NUMBER OF PAGES	36
&EPC	=	+	11

