Rittal - The System.

Faster – better – everywhere.





RX 9363.000 RiLineX Fuse-switch disconnector


State: 06.07.2025 (Source: rittal.com/bg-bg)



RX 9363.000 - RiLineX Fuse-switch disconnector

RiLineX NH fuse-switch disconnector in size 00 for mounting plates. The cover can be locked and prepared for a lead seal. It also has visual fuse monitoring. Integrated measuring points on the cover ensure safe voltage testing. NH fuse-switch disconnectors have a park position to make maintenance easier. Size M8 screw terminal connection.







Features

Model No.	RX 9363.000
Design	For mounting plate assembly
Benefits	Cover: can be locked and prepared for a lead seal
	Voltage test through separate opening
	Snap-on mounting up to 250 A and simple adjustment to busbar
	thickness 5/10 mm
	Tool-free changeover of the cable outlet
	Park position for simpler maintenance work
	High rated voltage 800 V ready
	All variants also available with electronic fuse monitoring
Material	Polyamide (PA 6)
	Fire protection corresponding to UL 94
	Contact tracks: Electrolytic copper, silver-plated
Colour	RAL 9005
	RAL 35745
for mounting plate assembly	Yes
Cable outlet	Top/bottom

© Rittal 2025 2

Features

Type of electrical connection	Screw M8
Rated insulation voltage	1000 kV
Rated operating current max.	160 A
Rated operating voltage	690 V AC
For NH size	00
Test specification	IEC/DIN EN 60 947-3 DIN EN 60 269-2 (fuse inserts)
Dimensions	Width: 106 mm Height: 194 mm Depth: 84 mm
Operating temperature range	-5 °C35 °C
Storage temperature range	-25 °C70 °C
Number of poles	3-pole
Utilisation category	AC-23B (400 V/100 A) AC-22B (500 V/100 A) DC-22B (250 V/100 A)
Contamination level	3
IP protection category to IEC 60 529	IP 2XB
Packs of	1 pc(s).
Net weight	0.755
Gross weight	0.785
Copper weight (kg per piece)	0.18
Customs tariff number	85369095
ETIM 9	EC001040

Approvals

© Rittal 2025 3

Approvals

Explanations

Declaration of conformity

© Rittal 2025