Rittal - The System.

Faster – better – everywhere.





RX 9363.005 RiLineX Fuse-switch disconnector

State: 20.07.2025 (Source: rittal.com/bg-bg)



RX 9363.005 - RiLineX Fuse-switch disconnector

RiLineX NH fuse-switch disconnector in size 00 for mounting plates. The cover can be locked and prepared for a lead seal. It also has visual fuse monitoring. Integrated measuring points on the cover ensure safe voltage testing. NH fuse-switch disconnectors have a park position to make maintenance easier. Size M8 screw terminal connection. Includes electronic fuse monitoring.



Features

Model No.	RX 9363.005
Design	For mounting plate assembly
Benefits	Cover: can be locked and prepared for a lead seal
	Voltage test through separate opening
	Tool-free changeover of the cable outlet
	Park position for simpler maintenance work
	High rated voltage 800 V ready
	All variants also available with electronic fuse monitoring
Material	Polyamide (PA 6)
	Fire protection corresponding to UL 94
	Contact tracks: Electrolytic copper, silver-plated
Colour	RAL 9005
	RAL 35745
Supply includes	Connectors for electronic fuse monitoring
for mounting plate assembly	Yes
Cable outlet	Top/bottom
Type of electrical connection	Screw M8
Rated insulation voltage	1000 kV

© Rittal 2025 2

Features

Rated operating current max.	160 A
Rated operating voltage	690 V AC
For NH size	00
Test specification	IEC/DIN EN 60 947-3 DIN EN 60 269-2 (fuse inserts)
Dimensions	Width: 106 mm Height: 229 mm Depth: 84 mm
Operating temperature range	-5 °C35 °C
Storage temperature range	-25 °C70 °C
Number of poles	3-pole
Utilisation category	AC-23B (400 V/100 A) AC-22B (500 V/100 A) DC-22B (250 V/100 A)
Contamination level	3
with electronic fuse monitoring	Yes
IP protection category to IEC 60 529	IP 2XB
Power dissipation (max.)	16 W
Packs of	1 pc(s).
Net weight	0.82
Gross weight	0.917
Copper weight (kg per piece)	0.18
Customs tariff number	85369095
ETIM 9	EC001040

Approvals

© Rittal 2025 3

Approvals

Explanations

Declaration of conformity

© Rittal 2025