Rittal - The System.

Faster – better – everywhere.





RX 9362.000 RiLineX NH fuse-switch disconnector

State: 2025-09-09 (Source: rittal.com/ca-en)



RX 9362.000 - RiLineX NH fuse-switch disconnector

RiLineX NH fuse-switch-disconnector in size 00 for 60 mm busbar systems. The cover is lockable, sealable and features visual fuse monitoring. The safe voltage test takes place via the integrated measurement points on the cover. The NH fuse-switch-disconnectors have a park position to simplify maintenance work. Connection version with size M8 screw connection. Cable outlet can be individually converted at the top or bottom.



Features

RX 9362.000
Cover, lockable and sealable Voltage test through separate opening Snap-on mounting up to 250 A and simple adjustment to busbar thickness 5/10 mm Tool-free changeover of the cable outlet Park position for simplified maintenance work All variants also available with electronic fuse monitoring
Polyamide (PA 6) Fire behavior corresponding to UL 94 Contact tracks: Electrolytic copper, silver-plated
RAL 9005 RAL 35745
60 mm
Top/bottom
Screw M8
160 A
690 V AC

© Rittal 2025 2

Features

For NH size	00
Test specification	IEC 60 947-3
	IEC 60 269-2 (fuse inserts)
Dimensions	Width: 106 mm
	Height: 195 mm
	Depth: 105 mm
Operating temperature range	-5 °C35 °C
Storage temperature range	-25 °C70 °C
Suitable for busbars	15 x 5/10
	20 x 5/10
	30 x 5/10
Suitable for busbar system	RiLine60
	RiLineX
Number of poles	3-pole
Utilisation category	AC-23B (400 V/100 A)
	AC-22B (500 V/100 A)
	DC-22B (250 V/100 A)
Contamination level	3
Protection category IP to IEC 60 529	IP 2XB
Power dissipation (max.)	19 W
Packaging unit	1 pc(s).
Net weight	1.015
Gross weight	1.023
Copper weight (kg per piece)	0.363
Customs tariff number	85369095
ETIM 9	EC001040

© Rittal 2025 3

Approvals

Explanations

Declaration of conformity

© Rittal 2025