Rittal - The System.

Faster – better – everywhere.





RX 9363.115 RiLineX NH fuse-switch disconnector

State: 2025-09-01 (Source: rittal.com/ca-en)



RX 9363.115 - RiLineX NH fuse-switch disconnector

RiLineX NH fuse-switch-disconnector in sizes 1 for mounting plates. The cover is lockable, sealable and features visual fuse monitoring. The safe voltage test takes place via the integrated measurement points on the cover. The NH fuse-switch-disconnectors have a park position to simplify maintenance work. Connection version with M10 screw connection. Including electronic fuse monitoring.

Features

Model No.	RX 9363.115
Version	For mounting panel assembly.
Benefits	Cover, lockable and sealable
	Voltage test through separate opening
	Tool-free changeover of the cable outlet
	Park position for simplified maintenance work
	All variants also available with electronic fuse monitoring
Material	Polyamide (PA 6)
	Fire behavior corresponding to UL 94
	Contact tracks: Electrolytic copper, silver-plated
Color	RAL 9005
	RAL 35745
Supply includes	Connectors for electronic fuse monitoring
for mounting plate assembly	Yes
Cable outlet	Top/bottom
Type of connection (electrical)	Screw M10
Rated insulation voltage	1,000 V
Rated operating current max.	250 A
Rated operating voltage	690 V AC
For NH size	1
	150 (0.047.0
Test specification	IEC 60 947-3

© Rittal 2025 2

Features

Dimensions	Width: 182 mm
	Height: 298 mm
	Depth: 111 mm
Operating temperature range	-5 °C35 °C
Storage temperature range	-25 °C70 °C
Number of poles	3-pole
Utilisation category	AC-23B (400 V/100 A)
	AC-22B (500 V/100 A)
	DC-22B (250 V/100 A)
	DC-21B (440 V/100 A)
Contamination level	3
With electronic fuse monitoring	Yes
Protection category IP to IEC 60 529	IP 2XB
Power dissipation (max.)	42 W
Packaging unit	1 pc(s).
Net weight	2.4
Gross weight	2.454
Copper weight (kg per piece)	0.57
Customs tariff number	85369095
ETIM 9	EC001040

Approvals

Declaration of conformity	Explanations
Decidiation of Comornity	illations

© Rittal 2025 3