

**Rittal – The System.**

Faster – better – everywhere.



**SV 9684.980**

**Contact hazard protection cover plate**

State: 9/07/2026 (Source: [rittal.com/ie-en](http://rittal.com/ie-en))

ENCLOSURES

POWER DISTRIBUTION

CLIMATE CONTROL

IT INFRASTRUCTURE

SOFTWARE & SERVICES

FRIEDHELM LOH GROUP



# SV 9684.980 - Contact hazard protection cover plate for enclosures with NH slimline fuse-switch disconnectors

To cover outgoing sections with NH slimline fuse-switch disconnectors so that they are safe from finger contact.

## Features

|                               |  |
|-------------------------------|--|
| Model No.                     | SV 9684.980  |
| Product description           | To cover outgoing sections with NH slimline fuse-switch disconnectors and busbar system in the rear enclosure section so that they are safe from finger contact (IP 2X). |
| Material                      | Sheet steel, 1.5 mm  |
| Surface finish                | Zinc-plated  |
| Supply includes               | 4 side panels (left/right side)<br>2 side panels (top/bottom)<br>Assembly parts  |
| Usable width for Flat-PLS     | 600 mm   |
| Note                          | The specified installation width when using the contact hazard protection cover only applies when using busbar support 9686.060/9686.070                                 |
| To fit                        | Enclosure type: TS<br>Width: = 800 mm  |
| Packs of                      | 1 pc(s).   |
| Net weight                    | 5.84 kg  |
| Gross weight                  | 6.74 kg  |
| PCF per pack (cradle-to-gate) | 25.7 kg CO2 eq (Cat B)   |
| Note on PCF category          | Category B: PCF value (cradle-to-gate) based on the product weight, approximately calculated and self-declared   |
| Customs tariff number         | 73269098   |
| ETIM 9                        | EC001638   |

# Features

---

ECLASS 8.0

27142116

---

Product description

SV Contact hazard protection cover, plate Form 2b (fuse-switch disconnecter, section), for VX (W: 800 mm)