Rittal - The System.

Faster – better – everywhere.





RX 9362.000 RiLineX Fuse-switch disconnector

State: 21/07/2025 (Source: rittal.com/ro-ro)



RX 9362.000 - RiLineX Fuse-switch disconnector

RiLineX NH fuse-switch disconnector in size 00 for 60 mm busbar systems. The cover can be locked and prepared for a lead seal. It also has visual fuse monitoring. Integrated measuring points on the cover ensure safe voltage testing. NH fuse-switch disconnectors have a park position to make maintenance easier. Size M8 screw terminal connection. Cable outlet can be at the top or bottom, as required.



Features

Model No.	RX 9362.000
Benefits	Cover: can be locked and prepared for a lead seal
	Voltage test through separate opening
	Snap-on mounting up to 250 A and simple adjustment to busbar
	thickness 5/10 mm
	Tool-free changeover of the cable outlet
	Park position for simpler maintenance work
	High rated voltage 800 V ready
	All variants also available with electronic fuse monitoring
Material	Polyamide (PA 6)
	Fire protection corresponding to UL 94
	Contact tracks: Electrolytic copper, silver-plated
Colour	RAL 9005
	RAL 35745
For bar systems with centre-to- centre spacing	60 mm
Cable outlet	Top/bottom
Type of electrical connection	Screw M8
Rated operating current max.	160 A

© Rittal 2025 2

Features

690 V AC 00 IEC/DIN EN 60 947-3
IEC/DIN EN 60 947-3
DIN EN 60 269-2 (fuse inserts)
Width: 106 mm Height: 195 mm Depth: 105 mm
-5 °C35 °C
-25 °C70 °C
15 x 5/10 20 x 5/10 30 x 5/10
RiLine60 RiLineX
3-pole
AC-23B (400 V/100 A) AC-22B (500 V/100 A) DC-22B (250 V/100 A)
3
IP 2XB
19 W
1 pc(s).
1.015
1.023
0.363
85369095
EC001040

© Rittal 2025 3

Approvals

Explanations

Declaration of conformity

© Rittal 2025