

**Rittal – The System.**

Faster – better – everywhere.



# SV 3071.000 Micro-switch

State: 04.06.2026 (Source: [rittal.com/ua-en](http://rittal.com/ua-en))

ENCLOSURES

POWER DISTRIBUTION

CLIMATE CONTROL

IT INFRASTRUCTURE

SOFTWARE & SERVICES

FRIEDHELM LOH GROUP



# SV 3071.000 - Micro-switch for NH fuse-switch disconnectors/NH slimline fuse-switch disconnectors (185 mm)

## Features

|                              |  |
|------------------------------|--|
| Model No.                    | SV 3071.000  |
| Product description          | To indicate the switch position of the NH unit (cover).  |
| Rated operating current max. | 5 A  |
| For size                     | NH fuse-switch disconnectors, size 000/00<br>NH slimline fuse-switch disconnectors, size 00 - 3 (185 mm)       |
| Packs of                     | 5 pc(s).   |
| Net weight                   | 0.015 kg   |
| Gross weight                 | 0.018 kg   |
| Customs tariff number        | 85366990   |
| ETIM 9                       | EC002270   |
| ETIM 8                       | EC001900   |
| ECLASS 8.0                   | 27400613   |
| Product description          | SV Micro-switch, for NH fuse-switch disconnectors size 000/00, NH slimline fuse-switch disconnectors, size 1-3 |

## Tender text

### Micro-switch

Micro-switch to indicate the switching position of the NH unit(lid unit).

For NH isolators: size 000, 00, 1

For NH fused isolators: size 00 up to Gr. 3

Maximum admissible current: 6A/250V