

Faster – better – everywhere.





# RX 9360.600

State: 21/07/2025 (Source: rittal.com/uae-en)



POWER DISTRIBUTION >> CLIMATE CONTROL

IT INFRASTRUCTURE SOFTWARE & SERVICES

#### RX 9360.600 -

CB component adaptor (3-pole, max. 160 A) for the RiLineX busbar platform and 60 mm busbar systems such as RiLine 60. The device width on the busbar system is 81 mm. The universal variant with U nuts offers maximum flexibility for switch mounting. The adaptor features tool-free, snap-on mounting with semi-automatic adjustment of the bar thickness between 5 and 10 mm. The cable outlet is easily converted to the top or bottom to suit individual requirements.

#### Features

Model No.	RX 9360.600
Design	universal
Benefits	Direct mounting of moulded-case circuit-breakers (MCCBs) on the board
	Tool-free changeover of the cable outlet
	Snap-on mounting up to 250 A and simple adjustment to busbar
	thickness 5/10 mm
	Fast, simple pre-assembly of standard market switch types outside
	of the enclosure
	High rated voltage 800 V ready
Material	Polyamide (PA 6)
	Fire protection corresponding to UL 94
Colour	RAL 9005
	RAL 35745
Supply includes	3 connection space covers
IP protection category to IEC 60 529	IP 2XB
Rated current max.	160 A
Rated current (UL)	125 A
Rated impulse withstand voltage Uimp	12 kV
Rated voltage	690 V AC
	690 V DC
	600 V AC (UL)

#### Features

Rated insulation voltage	1,000 V
Rated impulse withstand current	80 mA
Overvoltage category	4
Contamination level	3
Number of poles	3-pole
Cable outlet	Bottom
Type of electrical connection	Box terminal
To fit manufacturer (model)	<ul> <li>ABB (A1, S2, T1, T2, XT1, XT2, FD63/FD160)</li> <li>BTicino (M1 160)</li> <li>Chint (NM8N-125, NM1-63H, NM1-125H,NXM-63S, NXM-125S, NXM-160S, NXMS-160)</li> <li>Eaton (NZM1)</li> <li>Fuji Electric (BW125JAG-3P)</li> <li>Hager (P160)</li> <li>Himel (HDM3-100F/N, HDM3L-125)</li> <li>Hyundai Electric (100AF, 125AF, 125D, 160D AF)</li> <li>Legrand (DPX 160, DPX 250 ER, DPX<sup>3</sup> 160)</li> <li>LS Electric (100AF, 125AF, TE100, TD100, TE160, TD160)</li> <li>Mitsubishi (NF63-SV, NF125-SV)</li> <li>OEZ (BC160)</li> <li>Rockwell (140G-C2C3-D10, 140G-C2C3-D12, 140-C2E3-D16, 140G-H0F3-D10, 140G-H0F3-D12, 140G-H0F3-D16)</li> <li>Sassin (3SM8L-100)</li> <li>Schneider (NSC100N, NSXm50, NSXm100, NSXm160, NSXm250, NSE100)</li> <li>Schrack (MC1)</li> <li>Siemens (3VA10, 3VA11)</li> <li>Terasaki (E125, S125)</li> </ul>
To fit busbar system	RiLineX RiLine60
Fundamental frequency	5060 Hz
Ambient humidity (non- condensing)	1090 %

### Features

To fit busbars	15 x 5/10
	20 x 5/10
	30 x 5/10
Operating temperature range	-25 °C55 °C
Storage temperature range	-25 °C75 °C
Dimensions	Width: 81 mm
	Height: 252 mm
	Depth: 63 mm
Packs of	1 pc(s).
Net weight	0.92
Gross weight	1.048
Copper weight (kg per piece)	0.375
Customs tariff number	85369095
EAN	4028177997103
ETIM 9	EC001531

## Approvals

Approvals

UL + C-UL (listed)